



2006-01-01

Latency compensation control of computer based control systems

Aidan O'Dwyer

Dublin Institute of Technology, aidan.odwyer@dit.ie

Follow this and additional works at: <http://arrow.dit.ie/engscheleart>

 Part of the [Controls and Control Theory Commons](#)

Recommended Citation

O'Dwyer, Aidan : Latency compensation control of computer based control systems. Proceedings of the IT&T Conference, Institute of Technology, Carlow, October, 2006, pp.207-208.

This Conference Paper is brought to you for free and open access by the School of Electrical and Electronic Engineering at ARROW@DIT. It has been accepted for inclusion in Conference papers by an authorized administrator of ARROW@DIT. For more information, please contact yvonne.desmond@dit.ie, arrow.admin@dit.ie, brian.widdis@dit.ie.



This work is licensed under a [Creative Commons Attribution-NonCommercial-Share Alike 3.0 License](#)



Latency Compensation Control of Networked Computer Based Control Systems

Aidan O'Dwyer,

School of Control Systems and Electrical Engineering,

D.I.T. Kevin St., Dublin 8.

E-mail: aidan.odwyer@dit.ie

Abstract

This paper discusses the use of a modified Smith predictor for latency (i.e. time delay) compensation, to assist in the implementation of network computer based control systems. Such systems typically have a variable time delay associated with the transfer of information; the modified Smith predictor is robust to time delay variations.

1. Introduction

In building industrial control systems, it is increasingly common to use more sensors, actuators and microprocessor based controllers, to implement an intelligent digital system solution. As the number of devices grows, they need to exchange increasing amounts of data by means of various serial communications networks. Such networks (or fieldbuses) include Controller Area Networks (CAN), Profibus and Foundation Fieldbus. A practical problem with a networked control system is the time delay (or *latency*) associated with information transfer. This time delay may be deterministic, though it typically has a variable component (called *jitter*) [1], [2].

Networked control systems with such time delays may be compensated by using proportional integral derivative (PID) controllers, as reported previously [3]. Recently, the use of a dedicated time delay compensator, the Smith predictor, which is well known in the process control community, has been suggested for the application [4]-[6]. The motivation of this paper is to introduce the Smith predictor to the wider information technology and telecommunications community, and to introduce a modified Smith predictor, developed by the author, which allows a further improvement in performance.

2. The Smith Predictor

The design of controllers for processes with long time delays has been of interest to academics and practitioners for several decades. In a seminal contribution, Smith [7] proposed a technique that reduces the dominance of the delay term; a 'primary' controller, typically in PID form, may then be easily designed for the non-dominant delay process. This method, called the Smith predictor, has been the subject of numerous experimental and theoretical studies. A block diagram of the Smith predictor is provided in Figure 1 [8]. The *process* is the communications network. A mathematical process model is clearly required.




Figure 1. The Smith predictor.

3. The Modified Smith Predictor

When the primary controller is appropriately specified, the Smith predictor gives excellent response to setpoint variations. However, good response to disturbances (e.g. in link capacity) is important in the application. The author has developed a modified Smith predictor to improve the disturbance response by including an extra dynamic term in the outer feedback

loop of the Smith predictor. The parameters of this term are functions of the process model parameters.

Simulation results showing the operation of the method are given in Figures 2 to 4. The nominal process (G_p) is $2e^{-s}/1+8.5s+22.5s^2+18s^3$. The process model is specified using an appropriate identification method [9]. The process parameter values are allowed to vary between upper and lower limits; a $\pm 30\%$ variation in process time delay (latency) is allowed, with a similar variation in the other non-gain process parameters; a $\pm 40\%$ variation in the gain is permitted. The PI primary controller is specified using standard design techniques.




Figure 2. $G_p = 1.2e^{-0.7s}/1+5.9s+15.7s^2+12.6s^3$




Figure 3. $G_p = 2e^{-s}/1+8.5s+22.5s^2+18s^3$




Figure 4. $G_p = 2.8e^{-1.3s}/1+11s+29.3s^2+23.4s^3$

The results show that the modified Smith predictor facilitates a modest improvement in disturbance responses.

4. Conclusions

The Smith predictor and its modifications may be readily applied to the control of networked systems. These compensators are more complex than the standard PID control solution; however, their performance tends to be better than that achievable with the PID controller, particularly if the latency is large.

References

- [1] Irwin, G.W. (2004). "Research challenges in networked computer control", Plenary lecture, *Irish Signals and Systems Conference*, Queens University Belfast.
- [2] Lee, K.C., Lee, S. and Lee, H.H. (2004). "Implementation and PID tuning of network-based control systems via Profibus polling network", *Computer Standards and Interfaces*, 26, pp. 229-240.
- [3] O'Dwyer, A. (2005). "PID controller tuning of networked computer based control systems", *Proc. IT&T Conference*, pp. 273-274.
- [4] Kamrani, E., Momeni, H.R. and Sharafat, A.R. (2005). "A novel adaptive control system for stable teleoperation via internet", *Proc. IEEE Conference on Control Applications*, pp. 1164-1169.
- [5] Ohsaki, H., Watanabe, S. and Imase, M. (2005). "On dynamic source management mechanism using control theoretic approach for wide-area grid computing", *Proc. IEEE Conference on Control Applications*, pp. 891-897.
- [6] Mascolo, S. (2006). "Modelling the Internet congestion control using a Smith controller with input shaping", *Control Engineering Practice*, 14, pp. 425-435.
- [7] Smith, O.J.M. (1957). "Closer control of loops with dead time", *Chemical Engineering Progress*, 53, pp. 217-219.
- [8] VanDoren, V. (1996). "The Smith predictor: a process engineers crystal ball", *Control Engineering*. Available at <http://www.manufacturing.net/ctl/index.asp?layout=articlePrint&articleID=CA188333> [accessed 15 August 2006].
- [9] O'Dwyer, A. and Ringwood, J.V. (1995). "Model parameter and time delay estimation in the frequency domain", *Proc. 6th Irish Colloquium on DSP and Control*, pp. 39-46.